

Dual-Channel XLR Audio Mixer w/ Preamp (CoMica)

Overview

The Comica CVM-AX3 is a dual XLR/3.5mm/6.35mm Audio Mixer for shooting videos with DSLRs and camcorders. It is designed to support dynamic & passive microphones, real-time monitoring, & dual gain-control knobs. It provides a compact audio mixing solution.

The Comica CVM-AX3 battery supports 48V Phantom power with a working time of up to 6 hours. When the 48V Phantom power is off, the working time of a 9V battery is up to 40 hours.

The Comica AX3 allows independent gain control for each audio channel by simply adjusting the knobs to the desired level. This mixer breaks the single interface limit and adopts the latest multi-interface mixing technology. XLR/6.35mm/3.5 is unrestrained and more professional.

The AX3 includes two cold shoe mounts on both sides of the unit. This makes it easy to mount accessories such as LED lights, microphones, receivers, transmitters, monitors, articulating arms, and batteries.



Specifications

Audio Output	3.5mm audio output 3.5mm headphone output
Battery Stand-by Time	40 hrs. in 9V/6 hours in Phantom 48V
Battery Type	9V 6LR61/6F22 x 1
Frequency Response	20Hz~20kHz, ±1dB
Input Audio Format:	XLR x 2 (L/R), 6.35mm x 2 (L/R)
Noise Db	<0.02%, RL=2kΩ, f=20Hz~20kHz, Vo=1Vrms
Operation Temperature	0° C ~ +50° C
Storage Temperature	0° C ~ +60° C
UPC Code	6971120980869
Shipping Weight	2 lbs
Shipping Dimensions	7 x 7 x 4 in.
Product Weight	1 lb
Product Dimensions	4.8 x 2.8 x 2.4 in.

Special Features

- Supports Both 9V & 48V Phantom Power
- Includes Dual XLR/6.35mm/3.5mm Microphone Inputs
- Dual Gain Control Knobs
- Mono/Stereo Output Switch
- Supports Real-time Monitoring
- Three Cold Shoe Connectors Ideal For Mounting Accessories
- Made of Aluminum-Alloy

What's Included

- 1 x Audio mixer
- 1 x 3.5mm Audio Output Cable
- 1 x Cold Shoe Mount
- 1 x User Manual
- 1 x Warranty Card