

MSB8-3PT-KIT

QUICKSTART GUIDE

Mylo Soft Bi-Color 3-Point LED Light Kit



What's Included

- 1 x Light Bag
- 1 x Light Stand Bag
- 3 x Barn Doors
- 3 x Compact Light Stands
- 3 x Dual Battery Charger
- 3 x MSB8 Light Fixture
- 3 x Power Supply with Cable
- 3 x Yoke
- 6 x Sony "L" Series Style Batteries

CHECKED BY

ikan

www.ikancorp.com

support@ikancorp.com

713.272.8822

© 2017 ikan Corporation. All rights Reserved

Getting to know your Mylo Soft Bi-Color LED Light

Precautions:

Keep the fixture away from water and all flammable gasses or liquids

Use only the recommended batteries

Handle unit with care

DO NOT attempt to disassemble or repair the unit without first contacting the service department at ikancorp.com

Keep the unit clean and free of dust, it can be cleaned with a soft, dry cloth

Use only parts provided by the manufacturer

ALWAYS use caution when plugging in the fixture

Mounting the Mylo Soft to a Stand:

The Mylo Soft comes with pre-installed yoke and combo mount. This allows the fixture to easily sit and adjust on any stand. The yoke allows the light to move freely without obstruction. The Baby 5/8" and Junior 1 1/8" Combo Pin gives the user a wide range of stand options. The light can be mounted horizontally or vertically.

Power the LEDs:

The Mylo Soft light comes with an AC power supply and 6 foot cable. This allows the user to plug into any standard 120-240V electronic outlet. The Mylo Soft can be powered from one of two Sony "L" Series Style Batteries that are supplied with the unit.

Adjusting the Color & Brightness of the Light:

The Mylo Soft is controlled by the large yellow knob on the rear of the fixture. The knob was designed with the idea that it could be reached and adjusted when the light is up on the stand. The knob has two push settings.

1. The default setting is the brightness from 10-100% brightness.
2. By pressing in on the knob, the color temperature can be adjusted from 3200K-5600K.

Mylo Battery Options:

The dual battery charger allows you to charge both batteries at the same time.

Connect the power cable to the AC charger and plug it into a wall.

1. Place one or both battery packs into the charger and slide it towards the indicator lights.
2. The indicator lights will illuminate with how much charge is left on the battery.
3. The charger will begin charging once the battery is fully inserted into the charger. (Note: The battery is fully charged when all lights are solid red.

Attaching the battery pack to the back of the Mylo Soft can be done by placing the battery against the back of the Mylo battery port and sliding it forward.

Properly store the batteries when not in use. If the batteries will not be used for an extended period of time, run down the battery and store it with the Mylo Soft.

Charging Times:

	Normal Charging Time	Fully Charge Time
NP-F970	~373 minutes	~450 minutes

Be sure to charge the battery pack before you start using your Mylo Soft

We recommend charging the battery pack in an ambient temperature of between 50°F~86°F until the charge lamps are fully lit. If you charge the battery pack outside of this temperature range, you may not be able to charge it efficiently. Battery pack performance decreases when the temperature is 50°F or below, and the length of time you can use the battery pack becomes shorter. If temperatures are below 50°F we recommend that you put the battery in a pocket to warm it up, and then insert them into the Mylo Soft right before you turn the light fixture on.

About Battery Life

Battery capacity decreases over time and through repeated use. If you notice problems with the battery keeping a charge, it is probably time to replace it with a new one. Each battery's life is governed by storage, operating, and environmental conditions.

Specifications

MSB8 Fixture Specifications	
Battery Type	Sony "L" Series Style Batteries
Beam Angle	110°
Build Material	Heavy Duty Metal Construction
Cooling System	Passive Cooling
Dimming	Knob Control
Fixture Size	19 x 13 x 3.5 in.
Fixture Weight	8 lbs
Head Type	Bi-Color 3200K-5600K
Power Supply	Input: 100-240VAC Output: 12 VDC@5.0A
Yoke	Baby 5/8" - Junior 1-1/8" Combo Pin

Optional Accessories

Some other products that work well with the Mylo Soft Lights available from Ikan include:

HD-STND	Heavy Duty Light Stand
ROLLR-STND10	2-Stage Roller Stand 10 ft 6 in.
CP-STND-V3	Compact Light Stand Version 3
SW-04	Safety Wire
KCP-703	Stage Clamp w/ 16mm Stud

Learn More

More dynamic information at official website: www.ikancorp.com

Support

Contact email: support@ikancorp.com

CONDITIONS OF WARRANTY SERVICE

- Free service for one year from the day of purchase if the problem is caused by manufacturing errors.
- The components and maintenance service fee will be charged if the warranty period is expired.

Free Service will not be Provided in the Following Situations:(*Even if the product is still within the warranty period.)

- Damage caused by abuse or misuse, dismantling, or changes to the product not made by the company.
- Damage caused by natural disaster, abnormal voltage, and environmental factors, etc.