

IKC-H2S1

HDMI to SDI Converter QUICKSTART GUIDE



Checked by

CONDITIONS OF WARRANTY SERVICE

- Free service for one year from the day of purchase if the problem is caused by manufacturing errors.
- The components and maintenance service fee will be charged if the warranty period has expired.

Free Service will not be Provided in the Following Situations: (* Even if the product is still within the warranty period.)

- Damage caused by abuse or misuse, dismantling, or changes to the product not made by the company.
- Damage caused by natural disaster, abnormal voltage, and environmental factors etc.

IKC-H2S1

HDMI to SDI Converter QUICKSTART GUIDE



What's Included:

- ☐ 1 x HDMI to SDI Converter
- ☐ 1 x AC Adapter
- ☐ 2 x Mounting Brackets

SPECIFICATIONS:

Video Input	1 x BNC (HD/SD-SDI, 3G/1, 485G/270M)
Video Output	1 x SDI Loop-Through 1 x HDMI (with HDCP v 1.1), 19pin Female
Audio Output	External Audio Output (Stereo 3.5 pi)
HD Format Support	1920x1080 - 60p/59.94p/50p 1920x1080 - 60i, 59.94i, 50i, 30p, 29.97p, 25p, 24p, 23.98p 1920x1080 (30psf, 29.97psf, 25psf, 24psf, 23.98psf) 1280x720 - 60p, 59.94p, 50p
SD Format Support	NTSC, PAL
Power Requirement	4DC (7V-24V) or AC Adapter (100 ~ 230V, 50Hz/60Hz)
Power Consumption	6W
Operation Temperature	(-10°C ~ 40°C) (14°F ~ 104°F)
Operation Humidity	20% ~ 80% RH
Product Dimensions	4.6 x 3.9 x 1.4" (116.8 x 99 x 35.5mm)
Product Weight	.8 lb (.362 Kg)

ikan


www.ikancorp.com

713-272-8822

IKC-H2S1

HDMI to SDI Converter QUICKSTART GUIDE

INPUTS



OUTPUTS



DIP SWITCH SETTING

	DESCRIPTION	UP	DOWN
SW 1	LCD BACKLIGHT	OFF	ON
SW 2	LCD DISPLAY	RESOLUTION	LEVEL METER
SW 3	HDMI RANGE	0 ~ 255	16 ~ 235
SW 4	INPUT AUDIO SELECT	HDMI AUDIO	EXTERNAL
SW 5	AUDIO GROUP	CH1 ~ CH8	CH9 ~ CH16
SW 6	EXTERNAL AUDIO INPUT	PHONE JACK	OPTICAL
SW 7			
	EXTERNAL AUDIO INPUT		
	PHONE JACK	AES/EBU (BALANCE)	
	OPTICAL	SPDIF (2CH)	



CONDITIONS OF WARRANTY SERVICE

- Free service for one year from the day of purchase if the problem is caused by manufacturing errors.
- The components and maintenance service fee will be charged if the warranty period has expired.

Free Service will not be Provided in the Following Situations: (* Even if the product is still within the warranty period.)

- Damage caused by abuse or misuse, dismantling, or changes to the product not made by the company.
- Damage caused by natural disaster, abnormal voltage, and environmental factors etc.