

Wireless Handheld Microphone for WM200/WM300 Receivers (CoMica)

Overview

When using the Comica wireless microphone/transmitter in a noisy environment, you can cut out the low-frequency noise by adjusting the toggle switch on the microphone. The low cut function can effectively reduce environmental noise or wind noise.

The Comica Wireless Handheld Microphone Transmitter uses AA batteries as its power source to avoid the issue of having to recharge in the middle of a shoot. The working time is up to 3-5 hours.

The Comica Wireless Handheld Microphone Provides you with a variety of flexible wireless microphone system options. It can be synced to either the CVM-WM200 and CVM-WM300 series transmitters.

What You Need to Know When Using The CVM-WM300HTX

- The handheld mic/transmitter is designed for the 3.0.0/3.0.4 version of the CVM-WM300 A/C wireless microphone system. It is not compatible with the 1.0/1.1 version of the COMICA wireless microphone receiver.
- When using auto IR sync, please stay within one meter, otherwise, the signal may be too weak and the sync will not be successful.
- When using the stereo/mono mode switch, please preset the mode before using the microphone to avoid interference caused by switching during usage.
- When using this product in a short distance, it is recommended to set RF strength at 'LOW' to reduce the power consumption.



Specifications

Antenna Type	PCB Antenna
Audio Distortion	<0.5%
Battery Type	AA Batteries x 2pcs (Not included)
Channels	96
Dimensions	Ø2.1(Max) x 9.96 in.
Frequency Bands	Group A: 520.000MHz ~ 548.500MHz Group B: 550.000MHz 578.500MHz
Operation Temperature	32F ~ 122F
Signal-to-Noise Ratio	>65dB
Sound Delay	<20ms
Storage Temperature	-4F ~ 140F
Stray Radiation	<-60dBc
Transmission Power	10dBm / 15dBm
UPC Code	6971120980555
Shipping Weight	1.5 lb
Shipping Dimensions	14 x 8 x 6 in.

Special Features

- IR Sync for Quick Channel Selection
- Low Cut Filter Mode
- Adjustable RF Signal Strength
- Low Consumption/ Long Standby Time
- LCD Display
- Made of Aluminum

What's Included

1 x Wireless Microphone/Transmitter

Optional Accessories

- CVM-WM300A** Dual Transmitter Lavalier Microphone Kit (Li-Ion)
- CVM-WM200A** Dual Transmitter Lavalier Microphone Kit (AA)