

## Dual-Transmitter Lavalier Microphone Kit (AA) (Comica)

### Overview

The CVM-WM200A is a dual-transmitter and receiver wireless microphone kit from Comica. This kit runs on AA batteries (not included) and has a maximum range of 120m.

To begin using this kit, take out the transmitters and receiver and install 2 AA batteries in each unit. On the transmitters, use the large switch on the side to designate which unit is the A unit and which is the B. Then, you can either assign each a channel manually or use the IR search function to allow the transmitters and receiver to identify which channel has the least amount of interference and automatically assign themselves to that channel. Attach each unit to the user via belt clip, camera cold shoe mount, or an accessory arm via the 1/4-20 mount on the back.

Next, attach the included lavalier microphones to the two transmitters and clip them onto the subjects. Use any of the three included adapters to attach the receiver to the camera, speaker, mixer, or recorder that will be receiving the signal. For real-time audio monitoring, headphones can be inserted into the receiver, next to the Line Out port. Take a test sample of the audio, and begin recording! When you are done, the entire kit and all of its accessories fit neatly into the included hard case.



### Special Features

- 120m maximum range
- Receiver handles 2 transmitter groups simultaneously
- Single-switch control alternates transmitter between A and B groups
- Each transmitter and receiver operates on 2 AA batteries (not included)
- Live signal level monitoring on transmitters and receiver
- 96 channels to choose from between A and B groups
- IR channel syncing
- RF signal has adjustable power settings for close/long range

### What's Included

1x 3.5mm Male-to-Male Output Cable (TRRS)	1x Hard Storage/Transport Case
1x 3.5mm Male-to-Male Output Cable (TRS)	2x Lavalier Microphones W/ 3.5mm Connectors
1x 3.5mm To XLR Male-to-Male Output Cable	2x Transmitters
1x Dual-Group Receiver	2x Wind Muffs
	3x Camera Cold Shoe Mounts
	3x Removable Belt Clips

### Optional Accessories

**EI-A32** Quick Release Accessory Mount (E-Image)

### Specifications

Antenna Type	>65db
Audio Distortion	<0.5%
Battery Operating Time	~10 hrs. (standby)
Battery Type	2x AA batteries per Receiver/Transmitter (not included)
Channels	48
Frequency Range	Group A: 520~548.5MHz Group B: 550~578.5MHz
Inputs	3.5mm
Outputs	3.5mm
Receiving Sensitivity	-95dBm
Shipping Dimensions	14.5 x 10.25 x 3.5 in.
Shipping Weight	5 lb.
Sound Delay	<20ms
Stray Radiation	< -60dBc
Transmitting Power	10dBm/15dBm
UPC Code	6971120980388