

## Talent Monitor Add On Kit for PT4900



### What's Included

- 1 x Teleprompter Monitor w/ Aluminum Chassis
- 1 x Power Adapter with Cable
- 1 x VESA Monitor Mount
- 1 x 15mm Rod Adapter
- 1 x Mounting Knob
- 4 x 10mm Screws
- 4 x 15mm Screws
- 2 x Large Screws
- 4 x Riser Washers
- 1 x Adjustable Plate

## Assembly Steps

### Setting Up the Talent Monitor

Using the shorter 4 x 10mm Screws, attach the VESA Monitor Mount. Make sure that the long end of the VESA Monitor Mount is pointing in the direction of the power button like the image above. Use the Mounting Knob to tighten the 15mm Rod Adapter to the VESA Monitor Mount.



### Setting Up the Teleprompter Monitor (Monitor from the PT4900)

If the mounting brackets were previously installed on the teleprompter monitor, remove those screws. Using the longer 4 x 15mm Screws and 4 x Riser Washers attach the mounting brackets with the washers between the bracket and monitor like the image below.



## Attaching the Talent Monitor

After both the talent monitor and teleprompter monitor are set up, slide the talent monitor on to the PT4900.

**\*WARNING\*** We recommend at least 1 inch of rod should be left inside the teleprompter base.



# Specifications

## PT19-TM

19" High-Bright Teleprompter Monitor

Aspect Ratio	4:3
Brightness	1000 cd/m2
Screen Size	19"
Video Inputs	Composite BNC, VGA, HDMI
Input Voltage	DC 12v / 4A
Power Consumption	10 w
Product Weight	12 lbs
Product Dimensions	17" x 15" x 1"
Native Resolution	1280 x 1024
Shipping Weight	14 lbs
Shipping Dimensions	24" x 20" x 4"
Viewing Angle	160° (H) / 170° (V)
UPC	847983033201
Build Material	Aluminum Chassis

## Supported Video Signals

HDMI

720x480i & 720x480p @ 59.94, 60 Hz

720x576i & 720x576p @ 50 Hz

1280x720p @ 50, 59.94, 60 Hz

1920x1080i @ 50, 59.94, 60 Hz

1920x1080psf @ 24, 25, 29.97, 30 Hz

1920x1080p @ 23.98, 24, 25, 29.97, 30, 50, 59.94, 60 Hz

## Optional Accessories

Some other products that work well with this item available from Ikan include:

**PT4900** 19" High Bright Beam Splitter Teleprompter

## Learn More

More dynamic information at official website: [www.ikancorp.com](http://www.ikancorp.com)

## Support

Contact email: [support@ikancorp.com](mailto:support@ikancorp.com)

---

### CONDITIONS OF WARRANTY SERVICE

- Free service for one year from the day of purchase if the problem is caused by manufacturing errors.
- The components and maintenance service fee will be charged if the warranty period is expired.

#### **Free Service will not be Provided in the Following Situations:(\*Even if the product is still within the warranty period.)**

- Damage caused by abuse or misuse, dismantling, or changes to the product not made by the company.
- Damage caused by natural disaster, abnormal voltage, and environmental factors, etc.

©2019 Ikan International. All rights reserved.

